

<b>INLAND POWER &amp; LIGHT</b>
<b>APPROVED SELF-CONTAINED METER SOCKET</b>

SERVICE CAPACITY (AMPS)	MANUFACTURER	4 TERMINAL	SOCKET TYPE 5 TERMINAL	7 TERMINAL
100	C/AW (MCC TYPE)	121314	121315	NOT APPROVED
	MILBANK	U3504-XL	U3504XL ST8K2	
200 (120/240V)	C/AW (MCC TYPE)	U264	U264 & 50365	
	MILBANK	U3514-XL U1211-RRL	U1211-RxL K3866 U3415-XL ST8K2	U7423RXL U3517-XL
	L+G (MCC TYPE)	HQ-4G HQ-4GU HQ-4S	HQ-5 HQ-5U HQ-5S	HQ-7 (OH) HQ-7U (UG) HQ-7S (OH/UG)
200 (277/480V)	MILBANK	124TB	125TB	127TB MCC SAFETY SOCKET
	SIEMENS	M524TB	M525TB	M527TB MCC SAFETY SOCKET
400 RESIDENTIAL AND COMMERCIAL SOCKETS (ALL NEED TO BE MCC)	C/AW	324 N U4042 MCC		
	MILBANK	U33251 0 200 CB U11290 0 K3L K2L U3548-X (OH/UG) U1797X 0 K3L K2L	U1079R (OH)	U4911-X-BL
	L+G	HQ-4D		H588-K7 with lever bypass
	CUTLER/HAMMER	UTH4300TCH UTH4300ACH		UTTH736TCH
3PHASE CT RATED SOCKET (WYE)	MILBANK	UC3423-XL		
	C/AW	121413		
3PHASE CT RATED SOCKET (DELTA)	MILBANK	UC3428-XL		
	C/AW	12148		

**Special Instructions:**

- (1) Commercial meter sockets not listed must be individually approved by the Meter Department.
- (2) Meter modules with slide type and horn style bypasses are **NOT** approved.
- (3) **480V self-contained requires a safety socket.**
- (4) 5 and 7 terminal 3 phase sockets must have a lever bypass.
- (5) 400 amp meter bases requested to have a lever bypass.