

CT Enclosure

- Type 3R, ANSI 61 gray
- Removable hinged or non-hinged door(s) w/ sealing and locking provisions
- Service Ampacity: 401-800 Amps
- Cabinet WxHxD: 36x36x11 (min)

CT Landing Platforms

Part #'s or Equivalent

- For bar type ANSI C12.11 CT's
- 600V, 50kA AIC
- Line & Load side Mechanical Lugs


Cooper B-Line	Milbank
6019 HEL	K4729

Approved 5 Terminal, 100A Meter Socket

Manufacturer	Part#
Cooper B Line	U121315
Milbank	U3504XL(5TBK2) fifth terminal kit

Notes:

- 1) The customer supplies and install the current transformer enclosure, landing platform and meter base. IPL supplies and installs the current transformer, instrument wiring and meter.
- 2) IPL will supply, install and connect conductor to the line side only on UNDERGROUND services. The customer supplies, installs and connects conductor on OVERHEAD services.

ENGINEER:		1 PHASE CT METERING 401-800 AMP SERVICE				 INLAND POWER AND LIGHT CO.			
REVISED	IPL APR-13								PERM 1P-401-800